Nokia USB Product IDs

USB Product ID's for Nokia Devices

Last updated: 2008-11-25

Product Name	Hardware Name	USB PID	USB Mode	OS	Port	Cable
3109	RM-274;RM-275	0x0063	Mass Storage	S40	Mini USB	DKE-2
3109	RM-274;RM-275	0x0064	PC Suite (WMC)	S40	Mini USB	DKE-2
3109	RM-274;RM-275	0x0065	SICD for PictBridge and MTP	S40	Mini USB	DKE-2
3110	RM-237	0x005d	Mass Storage	S40	Mini USB	DKE-2
3110	RM-237	0x005e	PC Suite (WMC)	S40	Mini USB	DKE-2
3110	RM-237	0x005f	SICD for PictBridge and MTP	S40	Mini USB	DKE-2
3155	RM-41	0x043B	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
3230	RM-51	0x0421	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
3250	RM-40 US; RM-38 EU	0x042D	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
3250	RM-40 US; RM-38 EU	0x0460	SICD for PictBridge	S60	Pop-Port	CA-53 (DKU-2)
3250	RM-40 US; RM-38 EU	0x0462	MTP	S60	Pop-Port	CA-53 (DKU-2)
3250	RM-40 US; RM-38 EU	0x042E	Mass Storage	S60	Pop-Port	CA-53 (DKU-2)
3500	RM-272; RM-273	0x0060	Mass Storage	S40	Mini USB	DKE-2
3500	RM-272; RM-273	0x0061	PC Suite (WMC)	S40	Mini USB	DKE-2
3500	RM-272; RM-273	0x0062	SICD for PictBridge and MTP	S40	Mini USB	DKE-2
3555	RM-270	0x004c	Mass Storage	S40	Micro USB	CA-101
3555	RM-270	0x004d	SICD for PictBridge and MTP	S40	Micro USB	CA-101
3555	RM-270	0x004e	PC Suite (WMC)	S40	Micro USB	CA-101
3555	RM-277	0x004f	Mass Storage	S40	Micro USB	CA-101
3555	RM-277	0x0050	SICD for PictBridge and MTP	S40	Micro USB	CA-101
3555	RM-277	0x0051	PC Suite (WMC)	S40	Micro USB	CA-101
3555	RM-257	0x001f	PC Suite (WMC)	S40	Micro USB	CA-101
3555	RM-257	0x0020	Mass Storage	S40	Micro USB	CA-101
3555	RM-257	0x0021	SICD for PictBridge and MTP	S40	Micro USB	CA-101
5200	RM-174	0x04BC	PC Suite (WMC)	S40	Mini USB	DKE-2
5200	RM-174	0x04BD	Mass Storage	S40	Mini USB	DKE-2
5200	RM-174	0x04BE	SICD for PictBridge and MTP	S40	Mini USB	DKE-2
5300	RM-146	0x04B8	PC Suite (WMC)	S40	Mini USB	DKE-2
5300	RM-146	0x04B9	Mass Storage	S40	Mini USB	DKE-2
5300	RM-146	0x04BA	SICD for PictBridge and MTP	S40	Mini USB	DKE-2
5310	RM-303;RM-304	0x006a	Mass Storage	S40	Micro USB	CA-101
5310	RM-303;RM-304	0x006b	PC Suite (WMC)	S40	Micro USB	CA-101
5310	RM-303;RM-304	0x006c	SICD for PictBridge and MTP	S40	Micro USB	CA-101
5310	RM-303;RM-304	0x00bb	Mass Storage	S40	Micro USB	CA-101
5500	RM-86	0x04D8	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
5500	RM-86	0x04D9	Mass Storage	S60	Pop-Port	CA-53 (DKU-2)
5500	RM-86	0x04DA	MTP	S60	Pop-Port	CA-53 (DKU-2)
5500	RM-86	0x04DB	SICD for PictBridge	S60	Pop-Port	CA-53 (DKU-2)
5700	RM-230	0x04B2	PC Suite (WMC)	S60	Mini USB	DKE-2
5700	RM-230	0x04B3	Mass Storage	S60	Mini USB	DKE-2
5700	RM-230	0x04B4	MTP	S60	Mini USB	DKE-2
6051	RM-200	0x0058	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6051	RM-200	0x0059	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6051	RM-200	0x005a	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6085	RM-198	0x04B5	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6085	RM-198	0x04B6	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6085	RM-198	0x04B7	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6086	RM-188	0x04AF	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6086	RM-188	0x04B0	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6086	RM-188	0x04B1	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6111	RM-82	0x0456	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6111	RM-82	0x0457	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6111	RM-82	0x0458	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6111	RM-82	0x0459	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6125	RM-178	0x04A9	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6125	RM-178	0x04AA	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6125	RM-178	0x04AB	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6126	RM-126	0x04C0	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6131	RM-115	0x047B	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6131	RM-115	0x047C	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6131	RM-115	0x047D	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6133	RM-173	0x04C1	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6136	RM-106; RM-199	0x0441	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6136	RM-106; RM-199	0x0442	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6136	RM-106; RM-199	0x0463	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6151	P2913	0x04D2	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6151	P2913	0x04D3	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6151	P2913	0x04D4	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6155	RM-59	0x043C	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6155	RM-59	0x044A	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6165	RM-125	0x0464	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6165	RM-125	0x0465	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6170	RM-47	0x0416	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6175	RM-120	0x0468	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6175	RM-120	0x0469	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6178	RM-201	0x046C	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6178	RM-201	0x046D	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6205	RM-347	0x00a2	SICD for PictBridge and MTP+D211	other	Micro USB	CA-101
6205	RM-347	0x00a3	PC Suite (WMC)	other	Micro USB	CA-101
6205	RM-347	0x00a9	other	other	Micro USB	CA-101
6230	RM-72	0x040F	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6233	RM-145	0x0491	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6233	RM-145	0x0492	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6233	RM-145	0x0493	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6234	RM-123	0x0494	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6234	RM-123	0x0495	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6234	RM-123	0x0496	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6235	RM-60	0x041F	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6260	RM-25	0x0413	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
6263	RM-207	0x0012	PC Suite (WMC)	S40	Mini USB	DKE-2
6263	RM-207	0x0013	Mass Storage	S40	Mini USB	DKE-2
6263	RM-207	0x0014	SICD for PictBridge and MTP	S40	Mini USB	DKE-2
6265	RM-66	0x0437	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6265	RM-66	0x0438	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)

(C) Copyright Nokia 2013. All rights reserved.

6265	RM-66	0x044B	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6267	RM-210	0x0015	PC Suite (WMC)	S40	Mini USB	DKE-2
6267	RM-210	0x0016	Mass Storage	S40	Mini USB	DKE-2
6267	RM-210	0x0017	SICD for PictBridge and MTP	S40	Mini USB	DKE-2
6270	RM-56	0x043D	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6270	RM-56	0x043E	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6270	RM-56	0x0461	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6280	RM-78	0x045A	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6280	RM-78	0x045B	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6280	RM-78	0x045C	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6280	RM-79	0x045D	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6280	RM-79	0x045E	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6280	RM-79	0x045F	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6288	RM-78	0x0018	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6288	RM-78	0x0019	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6288	RM-78	0x001a	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6288	RM-268	0x0030	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6288	RM-268	0x0031	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6288	RM-268	0x0032	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6290	RM-176	0x04A5	PC Suite (WMC)	S60	Mini USB	DKE-2
6290	RM-176	0x04A6	Mass Storage	S60	Mini USB	DKE-2
6290	RM-176	0x04A7	SICD for PictBridge	S60	Mini USB	DKE-2
6290	RM-176	0x04A8	MTP	S60	Mini USB	DKE-2
6300	RM-217	0x04F9	PC Suite (WMC)	S40	Mini USB	DKE-2
6300	RM-217	0x04FA	Mass Storage	S40	Mini USB	DKE-2
6300	RM-217	0x04FB	SICD for PictBridge and MTP	S40	Mini USB	DKE-2
6301	RM-322	0x0089	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6301	RM-322	0x008a	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6301	RM-322	0x008b	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6555	RM-289	0x0003	Mass Storage	S40	Micro USB	CA-101
6555	RM-289	0x001b	PC Suite (WMC)	S40	other	RM-289
6555	RM-289	0x0022	SICD for PictBridge and MTP	S40	Micro USB	CA-101
6555	RM-271	0x0047	PC Suite (WMC)	S40	Micro USB	CA-101
6555	RM-271	0x0048	Mass Storage	S40	Micro USB	CA-101
6555	RM-271	0x0046	SICD for PictBridge and MTP	S40	Micro USB	CA-101
6620	NHL-12	0x040D	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
6630	NHL-12	0x0410	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
6650	RM-324	0x009d	Mass Storage	S60	Micro USB	CA-101
6650	RM-324	0x009e	MTP	S60	Micro USB	CA-101
6650	RM-324	0x009f	SICD for PictBridge	S60	Micro USB	CA-101
6650	RM-324	0x00a0	PC Suite (WMC)	S60	Micro USB	CA-101
6650	RM-324	0x00a1	IP passthrough	S60	Micro USB	CA-101
6680	RM-36	0x041E	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
6680	RM-36	0x0450	SICD for PictBridge	S60	Pop-Port	CA-53 (DKU-2)
6681	RM-57	0x0422	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
6682	RM-58	0x0423	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
7270	RM-8	0x0417	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
7370	RM-70	0x0414	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
7370	RM-70	0x047A	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
7373	RM-209	0x04F6	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
7373	RM-209	0x04F7	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
7373	RM-209	0x04F8	SICD for PictBridge and MTP+D189	S40	Pop-Port	CA-53 (DKU-2)
7390	RM-140	0x0489	PC Suite (WMC)	S40	Mini USB	DKE-2
7390	RM-140	0x048A	Mass Storage	S40	Mini USB	DKE-2
7390	RM-140	0x048B	SICD for PictBridge and MTP	S40	Mini USB	DKE-2
7500	RM-249	0x0067	Mass Storage	S40	Mini USB	DKE-2
7500	RM-249	0x0068	PC Suite (WMC)	S40	Mini USB	DKE-2
7500	RM-249	0x0069	SICD for PictBridge and MTP	S40	Mini USB	DKE-2
7610	RH-51;RH-52	0x0411	PC Suite (WMC)	S60	Mini USB	DKE-2
7650	NHL-2NA	0x0401	PC Suite (WMC)	S40	Mini USB	DKE-2
7710	RM-12	0x041C	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
7900	RM-264	0x003e	Mass Storage	S40	Micro USB	CA-101
7900	RM-264	0x003f	SICD for PictBridge and MTP	S40	Micro USB	CA-101
7900	RM-264	0x0040	PC Suite (WMC)	S40	Micro USB	CA-101
8800	RM-233	0x000b	PC Suite (WMC)	S40	Micro USB	CA-101
8800	RM-233	0x000c	Mass Storage	S40	Micro USB	CA-101
8800	RM-233	0x000d	SICD for PictBridge and MTP	S40	Micro USB	CA-101
9300	RA-4	0x0415	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
9300	RA-4	0x041B	IP passthrough	S60	Pop-Port	CA-53 (DKU-2)
9500	RA-2	0x0405	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
9500	RA-2	0x041A	IP passthrough	S60	Pop-Port	CA-53 (DKU-2)
2855; 2855i	RM-124	0x048C	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
2855; 2855i	RM-124	0x048D	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
2865; 2865i	RM-193	0x04DC	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
2865; 2865i	RM-193	0x04DD	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
2875; 2875i	RM-221	0x04FC	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
2875; 2875i	RM-221	0x04FD	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
3110e	RM-237	0x00bc	Mass Storage	S40	Mini USB	DKE-2
3110e	RM-237	0x00bd	PC Suite (WMC)	S40	Mini USB	DKE-2
3110e	RM-237	0x00be	SICD for PictBridge and MTP	S40	Mini USB	DKE-2
3120 classic	RM-366	0x00ac	Mass Storage	S40	Micro USB	CA-101
3120 classic	RM-366	0x00ad	SICD for PictBridge and MTP	S40	Micro USB	CA-101
3120 classic	RM-366	0x00ae	PC Suite (WMC)	S40	Micro USB	CA-101
3600 Slide	RM-352 (900MHz)	0x00bf	PC Suite (WMC)	S40	Micro USB	CA-101
3600 Slide	RM-352 (900MHz)	0x00c0	SICD for PictBridge and MTP	S40	Micro USB	CA-101
3600 Slide	RM-352 (900MHz)	0x00c1	Mass Storage	S40	Micro USB	CA-101
3600 Slide	RM-353 (850MHz)	0x00bf	PC Suite (WMC)	S40	Micro USB	CA-101
3600 Slide	RM-353 (850MHz)	0x00c0	SICD for PictBridge and MTP	S40	Micro USB	CA-101
3600 Slide	RM-353 (850MHz)	0x00c1	Mass Storage	S40	Micro USB	CA-101
3600s (China)	RM-352	0x00f6	PC Suite (WMC)	S40	Micro USB	CA-101
3600s (China)	RM-352	0x00f7	SICD for PictBridge and MTP	S40	Micro USB	CA-101
3600s (China)	RM-352	0x00f8	Mass Storage	S40	Micro USB	CA-101
3602s	RM-352	0x01d8	Mass Storage	S40	Micro USB	CA-101
3602s	RM-352	0x01d9	PC Suite (WMC)	S40	Micro USB	CA-101
3602s	RM-352	0x01da	SICD for PictBridge and MTP	S40	Micro USB	CA-101
3610 fold	RM-429	0x0163	Mass Storage	S40	Micro USB	CA-101
3610 fold	RM-429	0x0164	SICD for PictBridge and MTP	S40	Micro USB	CA-101
3610 fold	RM-429	0x0165	PC Suite (WMC)	S40	Micro USB	CA-101
5220 (China)	RM-411	0x0140	PC Suite (WMC)	S40	Micro USB	CA-101
5220 (China)	RM-411	0x0146	Mass Storage	S40	Micro USB	CA-101
5220 (China)	RM-411	0x0147	SICD for PictBridge and MTP	S40	Micro USB	CA-101
5220 XpressMusic	RM-411; RM-410	0x00f0	PC Suite (WMC)	S40	Micro USB	CA-101
5220 XpressMusic	RM-411; RM-410	0x00f1	SICD for PictBridge and MTP	S40	Micro USB	CA-101
5220 XpressMusic	RM-411; RM-410	0x00f2	Mass Storage	S40	Micro USB	CA-101
5310 (China)	RM-303; RM-304	0x00a6	Mass Storage	S40	Micro USB	CA-101
5310 (China)	RM-303; RM-304	0x00a8	SICD for PictBridge and MTP	S40	Micro USB	CA-101
5310 (China)	RM-303; RM-304	0x00a7	PC Suite (WMC)	S40	Micro USB	CA-101
5320 XpressMusic	RM-409	0x00e9	PC Suite (WMC)	S60	Micro USB	CA-101
5320 XpressMusic	RM-409	0x00ea	MTP	S60	Micro USB	CA-101
5320 XpressMusic	RM-409	0x00eb	SICD for PictBridge and MTP+D242	S60	Micro USB	CA-101
5320 XpressMusic	RM-409	0x00ec	Mass Storage	S60	Micro USB	CA-101

(C) Copyright Nokia 2013. All rights reserved.

5320 XpressMusic (2G)	RM-416	0x00fd	Mass Storage	S60	Micro USB	CA-101
5320 XpressMusic (2G)	RM-416	0x00fe	MTP	S60	Micro USB	CA-101
5320 XpressMusic (2G)	RM-416	0x00ff	SICD for PictBridge	S60	Micro USB	CA-101
5320 XpressMusic (2G)	RM-416	0x0108	PC Suite (WMC)	S60	Micro USB	CA-101
5610 XpressMusic	RM-242	0x0024	Mass Storage	S40	Micro USB	CA-101
5610 XpressMusic	RM-242	0x0025	PC Suite (WMC)	S40	Micro USB	CA-101
5610 XpressMusic	RM-242	0x0028	SICD for PictBridge and MTP	S40	Micro USB	CA-101
5610 XpressMusic	RM-358 (China)	0x00ce	PC Suite (WMC)	S40	Micro USB	CA-101
5610 XpressMusic	RM-358 (China)	0x00cf	Mass Storage	S40	Micro USB	CA-101
5610 XpressMusic	RM-358 (China)	0x00d0	SICD for PictBridge and MTP	S40	Micro USB	CA-101
5610 XpressMusic LTA	RM-279	0x00c8	PC Suite (WMC)	S40	Micro USB	CA-101
5610 XpressMusic LTA	RM-279	0x00c9	Mass Storage	S40	Micro USB	CA-101
5610 XpressMusic LTA	RM-279	0x00ca	SICD for PictBridge and MTP	S40	Micro USB	CA-101
5610 XpressMusic TMO	RM-359	0x00cb	PC Suite (WMC)	S40	Micro USB	CA-101
5610 XpressMusic TMO	RM-359	0x00cc	Mass Storage	S40	Micro USB	CA-101
5610 XpressMusic TMO	RM-359	0x00cd	SICD for PictBridge and MTP	S40	Micro USB	CA-101
5800 XpressMusic	RM-356	0x0154	PC Suite (WMC)	S60	Micro USB	CA-101
5800 XpressMusic	RM-356	0x0155	MTP	S60	Micro USB	CA-101
5800 XpressMusic	RM-356	0x0156	Mass Storage	S60	Micro USB	CA-101
5800 XpressMusic	RM-356	0x0157	SICD for PictBridge	S60	Micro USB	CA-101
6110 Navigator (China)	RM-186	0x0131	Mass Storage	S60	Mini USB	DKE-2
6110 Navigator (China)	RM-186	0x0132	MTP	S60	Mini USB	DKE-2
6110 Navigator (China)	RM-186	0x0133	SICD for PictBridge and MTP	S60	Mini USB	DKE-2
6110 Navigator (China)	RM-186	0x0134	PC Suite (WMC)	S60	Mini USB	DKE-2
6110 Navigator	RM-122	0x046E	PC Suite (WMC)	S60	Mini USB	DKE-2
6110 Navigator	RM-122	0x046F	Mass Storage	S60	Mini USB	DKE-2
6110 Navigator	RM-122	0x0470	SICD for PictBridge	S60	Mini USB	DKE-2
6110 Navigator	RM-122	0x0471	MTP	S60	Mini USB	DKE-2
6120 classic	RM-243	0x002d	Mass Storage	S60	Mini USB	DKE-2
6120 classic	RM-243	0x002e	MTP	S60	Mini USB	DKE-2
6120 classic	RM-243	0x002f	PC Suite (WMC)	S60	Mini USB	DKE-2
6121 classic	RM-308	0x0086	Mass Storage	S60	Mini USB	DKE-2
6121 classic	RM-308	0x0087	MTP	S60	Mini USB	DKE-2
6121 classic	RM-308	0x0088	PC Suite (WMC)	S60	Mini USB	DKE-2
6124 classic	RM-422	0x00f9	Mass Storage	S60	Mini USB	DKE-2
6124 classic	RM-422	0x00fa	MTP	S60	Mini USB	DKE-2
6124 classic	RM-422	0x00fb	SICD for PictBridge	S60	Mini USB	DKE-2
6124 classic	RM-422	0x00fc	PC Suite (WMC)	S60	Mini USB	DKE-2
6131 NFC	RM-216	0x0004	IP passthrough	S40	Pop-Port	CA-53 (DKU-2)
6131 NFC	RM-216	0x0005	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6131 NFC	RM-216	0x0006	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6131 NFC	RM-216	0x001d	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6165i	RM-125	0x0466	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6165i	RM-125	0x0467	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6175i	RM-120	0x046A	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6175i	RM-120	0x046B	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6178i	RM-201	0x04E7	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6178i	RM-201	0x04E8	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6210 Navigator	RM-367	0x0097	Mass Storage	S60	Micro USB	CA-101
6210 Navigator	RM-367	0x0098	MTP	S60	Micro USB	CA-101
6210 Navigator	RM-367	0x0099	PC Suite (WMC)	S60	Micro USB	CA-101
6210 Navigator	RM-367	0x00a4	SICD for PictBridge	S60	Micro USB	CA-101
6210 Navigator	RM-419	0x0125	Mass Storage	S60	Micro USB	CA-101
6210 Navigator	RM-419	0x0126	MTP	S60	Micro USB	CA-101
6210 Navigator	RM-419	0x0127	SICD for PictBridge	S60	Micro USB	CA-101
6210 Navigator	RM-419	0x0128	PC Suite (WMC)	S60	Micro USB	CA-101
6220 classic	RM-328	0x008c	Mass Storage	S60	Micro USB	CA-101
6220 classic	RM-328	0x008d	MTP	S60	Micro USB	CA-101
6220 classic	RM-328	0x008e	SICD for PictBridge	S60	Micro USB	CA-101
6220 classic	RM-328	0x008f	PC Suite (WMC)	S60	Micro USB	CA-101
6220c	RM-387	0x0121	Mass Storage	S60	Micro USB	CA-101
6220c	RM-387	0x0122	MTP	S60	Micro USB	CA-101
6220c	RM-387	0x0123	SICD for PictBridge	S60	Micro USB	CA-101
6220c	RM-387	0x0124	PC Suite (WMC)	S60	Micro USB	CA-101
6230i	RM-72	0x0428	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6230i	RM-72	0x0429	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6245i	RM-134; 6245i	0x04C6	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6245i	RM-134; 6245i	0x04C7	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6245i	RM-134; 6245i	0x04C8	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6255;6255i	RM-19	0x0402	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6255;6255i	RM-19	0x04FF	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6275; 6275i	RM-154	0x04D5	PC Suite (WMC)	S40	Pop-Port	CA-53 (DKU-2)
6275; 6275i	RM-154	0x04D6	Mass Storage	S40	Pop-Port	CA-53 (DKU-2)
6275; 6275i	RM-154	0x04D7	SICD for PictBridge and MTP	S40	Pop-Port	CA-53 (DKU-2)
6300i	RM-322	0x00c2	Mass Storage	S40	Mini USB	DKE-2
6300i	RM-322	0x00c3	PC Suite (WMC)	S40	Mini USB	DKE-2
6300i	RM-322	0x00c4	SICD for PictBridge and MTP	S40	Mini USB	DKE-2
6500 2G	RM-278	0x00c5	PC Suite (WMC)	S40	Micro USB	CA-101
6500 2G	RM-278	0x00c6	Mass Storage	S40	Micro USB	CA-101
6500 2G	RM-278	0x00c7	SICD for PictBridge and MTP	S40	Micro USB	CA-101
6500 classic	RM-265	0x003b	Mass Storage	S40	Micro USB	CA-101
6500 classic	RM-265	0x003c	SICD for PictBridge and MTP	S40	Micro USB	CA-101
6500 classic	RM-265	0x003d	PC Suite (WMC)	S40	Micro USB	CA-101
6500 slider	RM-240	0x0023	Mass Storage	S40	Micro USB	CA-101
6500 slider	RM-240	0x0026	PC Suite (WMC)	S40	Micro USB	CA-101
6500 slider	RM-240	0x0027	SICD for PictBridge and MTP	S40	Micro USB	CA-101
6500c (China)	RM-397	0x00dd	Mass Storage	S40	Micro USB	CA-101
6500c (China)	RM-397	0x00de	SICD for PictBridge and MTP	S40	Micro USB	CA-101
6500c (China)	RM-397	0x00df	PC Suite (WMC)	S40	Micro USB	CA-101
6555c	RM-276	0x0049	Mass Storage	S40	Micro USB	CA-101
6555c	RM-276	0x004a	SICD for PictBridge and MTP	S40	Micro USB	CA-101
6555c	RM-276	0x004b	PC Suite (WMC)	S40	Micro USB	CA-101
6600 fold	RM-325	0x0052	Mass Storage	S40	Micro USB	CA-101
6600 fold	RM-325	0x0053	SICD for PictBridge and MTP	S40	Micro USB	CA-101
6600 fold	RM-325	0x0054	PC Suite (WMC)	S40	Micro USB	CA-101
6600 slide	RM-414(EU);RM-415(LTA)	0x00e6	Mass Storage	S40	Micro USB	CA-101
6600 slide	RM-414(EU);RM-415(LTA)	0x00e7	SICD for PictBridge and MTP	S40	Micro USB	CA-101
6600 slide	RM-414(EU);RM-415(LTA)	0x00e8	PC Suite (WMC)	S40	Micro USB	CA-101
6600s (china)	RM-415	0x01bb	Mass Storage	S40	Micro USB	CA-101
6600s (china)	RM-415	0x01bc	PC Suite (WMC)	S40	Micro USB	CA-101
6600s (china)	RM-415	0x01bd	SICD for PictBridge and MTP	S40	Micro USB	CA-101
6670b	RH-67;RH-68	0x041D	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
7210 Supernova	RM-436	0x017a	PC Suite (WMC)	S40	Micro USB	CA-101
7210 Supernova	RM-436	0x017b	Mass Storage	S40	Micro USB	CA-101
7210 Supernova	RM-436	0x017c	SICD for PictBridge and MTP	S40	Micro USB	CA-101
7310 Supernova	RM-378; RM-379	0x00ed	PC Suite (WMC)	S40	Micro USB	CA-101
7310 Supernova	RM-378; RM-379	0x00ee	SICD for PictBridge and MTP	S40	Micro USB	CA-101
7310 Supernova	RM-378; RM-379	0x00ef	Mass Storage	S40	Micro USB	CA-101
7610 Supernova	RM-354; RM-354	0x00f3	PC Suite (WMC)	S40	Micro USB	CA-101
7610 Supernova	RM-354; RM-355	0x00f4	SICD for PictBridge and MTP	S40	Micro USB	CA-101
7610 Supernova	RM-354; RM-355	0x00f5	Mass Storage	S40	Micro USB	CA-101

(C) Copyright Nokia 2013. All rights reserved.

770 Internet Tablet	SU-18	0x0431	Mass Storage	Linux	Mini USB	DKU-2
8600 luna; 8600i luna	RM-164	0x001e	Mass Storage	S40	Micro USB	CA-101
8600 luna; 8600i luna	RM-164	0x04F2	PC Suite (WMC)	S40	Micro USB	CA-101
8600 luna; 8600i luna	RM-164	0x04F3	SICD for PictBridge and MTP	S40	Micro USB	CA-101
9300i	RA-8	0x0453	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
9300i	RA-8	0x0454	IP Passthrough	S60	Pop-Port	CA-53 (DKU-2)
Ascent Ti (Vertu)	RM-267V	0x016e	Mass Storage	S40	Micro USB	CA-101
Ascent Ti (Vertu)	RM-267V	0x016f	SICD for PictBridge and MTP	S40	Micro USB	CA-101
Ascent Ti (Vertu)	RM-267V	0x0170	PC Suite (WMC)	S40	Micro USB	CA-101
Cable CA-42	CA-42	0x0802	Cable	Cable	CA-42	Cable
Cable DKU-5	DKU-5	0x0800	Cable	Cable	DKU-5	Cable
Cable DKU-6	DKU-6	0x0801	Cable	Cable	DKU-6	Cable
E50	RM-170; RM-171; RM-172	0x04C9	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
E50	RM-170; RM-171; RM-172	0x04CA	Mass Storage	S60	Pop-Port	CA-53 (DKU-2)
E51	RM-244	0x0041	Mass Storage	S60	Mini USB	DKE-2
E51	RM-244	0x0042	PC Suite (WMC)	S60	Mini USB	DKE-2
E60	RM-49	0x0419	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
E60	RM-49	0x0434	Mass Storage	S60	Pop-Port	CA-53 (DKU-2)
E60	RM-49	0x0436	IP passthrough	S60	Pop-Port	CA-53 (DKU-2)
E61	RM-89	0x044D	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
E61	RM-89	0x044E	Mass Storage	S60	Pop-Port	CA-53 (DKU-2)
E61	RM-89	0x044F	IP Passthrough	S60	Pop-Port	CA-53 (DKU-2)
E61i	RM-227	0x0001	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
E61i	RM-227	0x0002	Mass Storage	S60	Pop-Port	CA-53 (DKU-2)
E62	RM-88	0x0475	PC Suite (WMC)	S60	Mini USB	DKE-2
E62	RM-88	0x0476	Mass Storage	S60	Mini USB	DKE-2
E62	RM-88	0x0477	IP Passthrough	S60	Mini USB	DKE-2
E65	RM-208	0x0508	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
E65	RM-208	0x0509	Mass Storage	S60	Pop-Port	CA-53 (DKU-2)
E66	RM-343	0x00af	Mass Storage	S60	Micro USB	CA-101
E66	RM-343	0x00b0	PC Suite (WMC)	S60	Micro USB	CA-101
E66	RM-343	0x00e5	MTP	S60	Micro USB	CA-101
E70	RM-10	0x0418	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
E70	RM-10	0x0433	Mass Storage	S60	Pop-Port	CA-53 (DKU-2)
E70	RM-10	0x0435	IP passthrough	S60	Pop-Port	CA-53 (DKU-2)
E71	RM-346	0x00ab	PC Suite (WMC)	S60	Micro USB	CA-101
E71	RM-346	0x00e4	MTP	S60	Micro USB	CA-101
E71	RM-346	0x00aa	Mass Storage	S60	Micro USB	CA-101
E90	RA-6	0x04CF	Mass Storage	S60	Mini USB	DKE-2
E90	RA-6	0x04D0	IP Passthrough	S60	Mini USB	DKE-2
N70	RM-84	0x0451	SICD for PictBridge	S60	Pop-Port	CA-53 (DKU-2)
N70	RM-84	0x043A	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
N70	RM-99 (2G)	0x0443	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
N70	RM-99 (2G)	0x0452	SICD for PictBridge	S60	Pop-Port	CA-53 (DKU-2)
N71	RM-67	0x0424	SICD for PictBridge	S60	Pop-Port	CA-53 (DKU-2)
N71	RM-67	0x0425	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
N71	RM-67	0x042C	Mass Storage	S60	Pop-Port	CA-53 (DKU-2)
N71	RM-67	0x0480	MTP	S60	Pop-Port	CA-53 (DKU-2)
N72	RM-180	0x04C4	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
N72	RM-180	0x04C5	SICD for PictBridge	S60	Pop-Port	CA-53 (DKU-2)
N73	RM-132;RM-133	0x0486	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
N73	RM-132;RM-133	0x0487	Mass Storage	S60	Pop-Port	CA-53 (DKU-2)
N73	RM-132;RM-133	0x0488	SICD for PictBridge	S60	Pop-Port	CA-53 (DKU-2)
N73	RM-132;RM-133	0x04D1	MTP	S60	Pop-Port	CA-53 (DKU-2)
N75	RM-128	0x04DF	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
N75	RM-128	0x04E0	Mass Storage	S60	Pop-Port	CA-53 (DKU-2)
N75	RM-128	0x04E1	MTP	S60	Pop-Port	CA-53 (DKU-2)
N75	RM-128	0x04E2	SICD for PictBridge	S60	Pop-Port	CA-53 (DKU-2)
N76	RM-135	0x0481	PC Suite (WMC)	S60	Mini USB	DKE-2
N76	RM-135	0x0482	Mass Storage	S60	Mini USB	DKE-2
N76	RM-135	0x0483	SICD for PictBridge	S60	Mini USB	DKE-2
N76	RM-135	0x0484	MTP	S60	Mini USB	DKE-2
N77	RM-194; RM-195	0x000e	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
N77	RM-194; RM-195	0x000f	Mass Storage	S60	Pop-Port	CA-53 (DKU-2)
N77	RM-194; RM-195	0x0010	SICD for PictBridge	S60	Pop-Port	CA-53 (DKU-2)
N77	RM-194; RM-195	0x0011	MTP	S60	Pop-Port	CA-53 (DKU-2)
N78	RM-235	0x0077	IP passthrough	S60	Micro USB	CA-101
N78	RM-235	0x0078	Mass Storage	S60	Micro USB	CA-101
N78	RM-235	0x0079	MTP	S60	Micro USB	CA-101
N78	RM-235	0x007a	SICD for PictBridge	S60	Micro USB	CA-101
N78	RM-235	0x007b	PC Suite (WMC)	S60	Micro USB	CA-101
N80	RM-91;RM-92;RM-93	0x0445	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
N80	RM-91;RM-92;RM-93	0x0446	Mass Storage	S60	Pop-Port	CA-53 (DKU-2)
N80	RM-91;RM-92;RM-93	0x0447	Pictbridge	S60	Pop-Port	CA-53 (DKU-2)
N80	RM-91;RM-92;RM-93	0x04F1	MTP	S60	Pop-Port	CA-53 (DKU-2)
N800 Internet Tablet	RX-34	0x04C2	PC Suite (WMC)	Linux	Mini USB	DKE-2
N800 Internet Tablet	RX-34	0x04C3	Mass Storage	Linux	Mini USB	DKE-2
N81	RM-223;RM-179	0x0007	PC Suite (WMC)	S60	Micro USB	CA-101
N81	RM-223;RM-179	0x0008	Mass Storage	S60	Micro USB	CA-101
N81	RM-223;RM-179	0x0009	SICD for PictBridge	S60	Micro USB	CA-101
N81	RM-223;RM-179	0x000a	MTP	S60	Micro USB	CA-101
N810 Internet Tablet	RX-44	0x0096	Mass Storage	Linux	Micro USB	CA-101
N810 WiMax edition	RX-48	0x0189	Mass Storage	Linux	Micro USB	CA-101
N82	RM-314	0x0071	PC Suite (WMC)	S60	Micro USB	CA-101
N82	RM-314	0x0072	Mass Storage	S60	Micro USB	CA-101
N82	RM-314	0x0073	SICD for PictBridge	S60	Micro USB	CA-101
N82	RM-314	0x0074	MTP	S60	Micro USB	CA-101
N85	RM-333	0x0090	IP passthrough	S60	Micro USB	CA-101
N85	RM-333	0x0091	Mass Storage	S60	Micro USB	CA-101
N85	RM-333	0x0092	MTP	S60	Micro USB	CA-101
N85	RM-333	0x0093	SICD for PictBridge	S60	Micro USB	CA-101
N85	RM-333	0x0094	PC Suite (WMC)	S60	Micro USB	CA-101
N90	RM-42	0x0432	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
N90	RM-42	0x0455	SICD for PictBridge	S60	Pop-Port	CA-53 (DKU-2)
N91-1	RM-43	0x042F	PC Suite (WMC)	S60	Mini USB	DKE-2
N91-1	RM-43	0x0444	Mass Storage	S60	Mini USB	DKE-2
N91-1	RM-43	0x0485	MTP	S60	Mini USB	DKE-2
N92	RM-100	0x048E	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
N92	RM-100	0x0497	Mass Storage	S60	Pop-Port	CA-53 (DKU-2)
N92	RM-100	0x0498	SICD for PictBridge	S60	Pop-Port	CA-53 (DKU-2)
N92	RM-100	0x04DE	MTP	S60	Pop-Port	CA-53 (DKU-2)
N93	RM-55	0x0420	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
N93	RM-55	0x0448	Mass Storage	S60	Pop-Port	CA-53 (DKU-2)
N93	RM-55	0x0449	SICD for PictBridge	S60	Pop-Port	CA-53 (DKU-2)
N93	RM-55	0x0478	MTP	S60	Pop-Port	CA-53 (DKU-2)
N93i	RM-156	0x04E3	Mass Storage	S60	Pop-Port	CA-53 (DKU-2)
N93i	RM-156	0x04E4	SICD for PictBridge	S60	Pop-Port	CA-53 (DKU-2)
N93i	RM-156	0x04E5	MTP	S60	Pop-Port	CA-53 (DKU-2)
N93i	RM-156	0x04E6	PC Suite (WMC)	S60	Pop-Port	CA-53 (DKU-2)
N95	RM-159	0x04ED	Mass Storage	S60	Mini USB	DKE-2
N95	RM-159	0x04EE	SICD for PictBridge	S60	Mini USB	DKE-2

(C) Copyright Nokia 2013. All rights reserved.

N95	RM-159	0x04EF	MTP	S60	Mini USB	DKE-2
N95	RM-159	0x04F0	PC Suite (WMC)	S60	Mini USB	DKE-2
N95 8GB	RM-320	0x006d	Mass Storage	S60	Mini USB	DKE-2
N95 8GB	RM-320	0x006e	MTP	S60	Mini USB	DKE-2
N95 8GB	RM-320	0x006f	SICD for PictBridge	S60	Mini USB	DKE-2
N95 8GB	RM-320	0x0070	PC Suite (WMC)	S60	Mini USB	DKE-2
N96	RM-246; RM-247	0x0037	Mass Storage	S60	Micro USB	CA-101
N96	RM-246; RM-247	0x0038	SICD for PictBridge	S60	Micro USB	CA-101
N96	RM-246; RM-247	0x0039	MTP	S60	Micro USB	CA-101
N96	RM-246; RM-247	0x003a	PC Suite (WMC)	S60	Micro USB	CA-101
N96	RM-296; RM-297	0x0037	Mass Storage	S60	Micro USB	CA-101
N96	RM-296; RM-297	0x0038	SICD for PictBridge	S60	Micro USB	CA-101
N96	RM-296; RM-297	0x0039	MTP	S60	Micro USB	CA-101
N96	RM-296; RM-297	0x003a	PC Suite (WMC)	S60	Micro USB	CA-101
NM706i	RM-448	0x0169	Mass Storage	S60	Micro USB	CA-101
NM706i	RM-448	0x016a	MTP	S60	Micro USB	CA-101
Nokia 1508	RM-388	0x0162	Other	Other	Micro USB	CA-101
Nokia 5120 XpressMusic	RM-495; RM496	0x0207	Mass Storage	S40	Micro USB	CA-101
Nokia 5120 XpressMusic	RM-495; RM496	0x0208	PC Suite (WMC)	S40	Micro USB	CA-101
Nokia 5120 XpressMusic	RM-495; RM496	0x0209	SICD for PictBridge and MTP	S40	Micro USB	CA-101
Nokia 5120 XpressMusic	RM-495 (China)	0x020a	SICD for PictBridge and MTP	S40	Micro USB	CA-101
Nokia 5120 XpressMusic	RM-495 (China)	0x020b	PC Suite (WMC)	S40	Micro USB	CA-101
Nokia 5120 XpressMusic	RM-495 (China)	0x020c	Mass Storage	S40	Micro USB	CA-101
Nokia 6212 classic	RM-396	0x01fd	Mass Storage	S40	Micro USB	CA-101
Nokia 6212 classic	RM-396	0x01fe	PC Suite (WMC)	S40	Micro USB	CA-101
Nokia 6212 classic	RM-396	0x01ff	SICD for PictBridge and MTP	S40	Micro USB	CA-101
Nokia 7310c (China)	RM-378	0x0143	PC Suite (WMC)	S40	Micro USB	CA-101
Nokia 7310c (China)	RM-378	0x0144	Mass Storage	S40	Micro USB	CA-101
Nokia 7310c (China)	RM-378	0x0145	SICD for PictBridge and MTP	S40	Micro USB	CA-101
Nokia 7510 Supernova	RM-398	0x0139	PC Suite (WMC)	S40	Micro USB	CA-101
Nokia 7510 Supernova	RM-398; RM-399	0x013a	Mass Storage	S40	Micro USB	CA-101
Nokia 7510 Supernova	RM-398; RM-399	0x013b	SICD for PictBridge and MTP	S40	Micro USB	CA-101
Nokia 7510a	RM-398	0x013c	PC Suite (WMC)	S40	Micro USB	CA-101
Nokia 7510a	RM-398	0x013d	Mass Storage	S40	Micro USB	CA-101
Nokia 7510a	RM-398	0x013e	SICD for PictBridge and MTP	S40	Micro USB	CA-101
Signature (Vertu)	RM-266V	0x016b	Mass Storage	S40	Micro USB	CA-101
Signature (Vertu)	RM-266V	0x016c	SICD for PictBridge and MTP	S40	Micro USB	CA-101
Signature (Vertu)	RM-266V	0x016d	PC Suite (WMC)	S40	Micro USB	CA-101

(C) Copyright Nokia 2013. All rights reserved.

(C) Copyright Nokia 2013. All rights reserved.